

# LED T8 INTEGRATED TUBE LIGHT(SEAMLESS)+PLC

INT-1FT-PLC8W-CCT | INT-2FT-PLC15W-CCT | INT-3FT-PLC22W-CCT | INT-4FT-PLC30W-CCT | INT-8FT-PLC60W-CCT

## DESCRIPTION

T8 INTEGRATED TUBE | 1ft 2ft 3ft 4ft 8ft | 125lm/W | Seamless | Linkable & Plug and Play |  
PLC Smart Switch-Applicable

Can be used with  
PLC Smart Switch



## CONSTRUCTION

PC + Aluminum | T8 Integrated LED Tubes Seamless

## ELECTRICAL

Runs on 120-277V line voltage

## LINKABLE

The ability to link multiple tube lights together allows you to customize the lighting arrangement to suit your space perfectly, providing uniform lighting across larger areas.

## EASY INSTALLATION

The T8 LED Integrated Tube light doesn't need a ballast fixture, making setup easy. Just connect the provided connector and secure the fixture with the included clips and screws. This simple installation saves on maintenance and costs

## APPLICATIONS

From residential spaces to commercial establishments, these tube lights find utility in a wide range of settings, including homes, offices, retail stores, garage, workshops, basement and more.

## PLC SMART SWITCH

Control the lamp turn on/off, brightness(0%-100%), color temperature(2700K-6500K) and custom lighting mode.

## LISTING

ETL, DLC, FCC

## WARRANTY

5 Years Limited Warranty, Rated for 50,000 hours.

## FEATURES

Bulb Type	T8 LED
Size	1FT   2FT   3FT   4FT   8FT
Wattage (With PLC Smart Switch)	1FT: 8W(0%-100% Adjustable) 2FT: 15W(0%-100% Adjustable) 3FT: 22W(0%-100% Adjustable) 4FT: 30W(0%-100% Adjustable) 8FT: 60W(0%-100% Adjustable)
CCT (With PLC Smart Switch)	2700K-6500K(Linear adjustable)
Efficiency	125lm/W
PLC Smart Switch	Applicable
Input Voltage	120-277V AC
Frequency Range	50/60Hz
Linkable	Yes
Cover	Frosted / Clear
CRI	>80
PF	>0.95
THD	<=20%
Beam Angle	120°
IP Rating	IP 40
Lifetime	50,000 hours


## ORDERING INFORMATION

Model	Size	Wattage (With PLC Smart Switch)	Voltage	Lumens	Efficacy	CCT (With PLC Smart Switch)	Certifications
INT-1FT-PLC8W-CCT	1FT	8W (0%-100% Adjustable)	120-277V	1000lm	125 lm/W	2700K-6500K (Linear adjustable)	-
INT-2FT-PLC15W-CCT	2FT	15W (0%-100% Adjustable)	120-277V	1875lm	125 lm/W	2700K-6500K (Linear adjustable)	ETL
INT-3FT-PLC22W-CCT	3FT	22W (0%-100% Adjustable)	120-277V	2750lm	125 lm/W	2700K-6500K (Linear adjustable)	ETL
INT-4FT-PLC30W-CCT	4FT	30W (0%-100% Adjustable)	120-277V	3750lm	125 lm/W	2700K-6500K (Linear adjustable)	ETL/DLC
INT-8FT-PLC60W-CCT	8FT	60W (0%-100% Adjustable)	120-277V	7500lm	125 lm/W	2700K-6500K (Linear adjustable)	ETL/DLC

## PHYSICAL SPECIFICATIONS

Unit: mm/inch


### 1FT




### 2FT




### 3FT



### 4FT




### 8FT



Dimensional tolerances: (+1.5mm, -1.0mm)


## INSTALLATION INSTRUCTIONS

1




Confirm the buckle's position on the wall.

2



Screw the buckles on the wall.


3




Fix the light into the buckles

## CONNECTION INSTALLATION

### Method 1: Connector




Please find the connector in the accessories bag.



Plug the connector into the tube.

### Method 2: Middle Connector



Please find the middle connector, Plug the middle connector into the tube.

## Can be used with PLC Smart Switch



**SMART  
DIMMING**



**CCT  
ADJUSTABLE**



**SCENE  
MODEL**

### Status LED


· Provides connectivity and device status feedback.

### Brt.- (Darker)

· Dim lights.

### Ct. < (Warm)

· Decrease CCT.



### ON/OFF

· Press to toggle the light on and off.

### Brt.+ (Brighter)

· Brighten lights.

### Ct. > (White)


· Increase CCT.

### Mode

· With 3 scene modes adjustable.

## Wire Diagram

### Using with PLC Smart Switch



### MAX CONNECT TOTAL WATTAGE

	400W PLC Smart Switch	800W PLC Smart Switch	1200W PLC Smart Switch
AC 120V	400W	800W	1200W
AC 277V	800W	1600W	2400W



For safety standards, do not connect more than the rated power of the PLC smart Switch.